




STARLINK | FLAT HIGH PERFORMANCE KIT SETUP GUIDE




What's In The Box




Dish




Wedge Mount




Power Supply



Power Supply Mount


Starlink Cable
25 m
(82 ft)Ethernet Cable
5 m
(16.5 ft)AC Cable (Power Supply)
1.8 m
(6 ft)Sealing Washers
4xWashers
8xLock Nuts
4xScrews
4xWall Anchors
4xMachine Screws
4x
38.1 mm (1.5 in)Socket Head Bolts
2x
13 mm (1/2 in)Shoulder Bolts
2x

Thread Locker



Silicone Sealant

Recommended Tools



Drill / Impact Driver

Drill Bit
6.5 mm (1/4 in)Drill Bit
8 mm (5/16 in)

Pencil



7/16 in Socket



7/16 in Wrench

Philips Head
Screwdriver

Socket Wrench



5/32 in Hex Key



3/16 in Hex Key

For personalized advice or more details about Starlink Maritime, reach out to our team at
globalservice@hostmostgroup.com




1 | Download the Starlink App

Scan the QR code to download the Starlink App.



2 | Mounting Location

Your Starlink needs a clear view of the sky so it can stay connected with satellites as they move overhead. Objects that obstruct the connection between your Starlink and the satellite, such as a tree branch, pole, or roof, will cause service interruptions. Use the obstruction tool in the App to ensure you have selected a suitable mounting location.




For personalized advice or more details about Starlink Maritime, reach out to our team at
globalservice@hostmostgroup.com

3 | Mark the Pilot Holes

Mark the location of the four holes on your Wedge Mount using a pen or pencil.


The included machine screws can accommodate mounting surfaces up to 11.44 mm (0.3 in) thick.



4 | Drill the Pilot Holes

Drill the holes with a 6.5 mm (0.25 in) drill bit.


Remove burrs around holes and make sure the surface is free of debris.



5 | Apply Sealant and Screw in Mobility Mount


Place rubber washers over holes followed by mount. Install a washer on each of the four machine screws, liberally apply silicone sealant on the threads, and insert screws through mount and pre-drilled holes.

Install a washer and nut on the end of each machine screw and secure mount to surface. Use a 7/16 in socket and wrench to tighten screws to snug plus 1/4 turn. Do not overtighten.




6 | Install Shoulder Bolt

Install shoulder bolts into threaded holes near the cable port. Use a 5/32 in hex key to tighten bolts to hand tight.




7 | Lock Starlink onto Mount

Align shoulder bolts into the keyway on the bottom of the mount. Push down and slide Starlink forward to lock into place.




Once secured, fully tighten shoulder bolts.



8 | Secure Starlink


Wet threads of the 12.7 mm (0.5 in) socket head bolts with thread locker and install into the two remaining holes to secure Starlink. Use the 3/16 in hex key to tighten screws to snug plus 1/4 turn. Do not overtighten.

Ensure you are using the 12.7 mm (0.5 in) length bolts. Longer bolts can damage Starlink.



9 | Connect and Align Starlink

Plug the Starlink cable into the port on the bottom of the Starlink. Ensure the cable is fully plugged in and push the latch into locking position until you hear or feel a click.




If you have a Starlink router, step through the Starlink install process on the Starlink App.

If you have a compatible third-party router, follow the router's set up instructions.

1 | Mark Pilot Holes


Remove the power supply from its mount and select a mount location no more than 1.8 m (6ft) away from your power source.

Mark the location of the two holes on your Power Supply Mount using a pen or pencil.



2 | Drill the Pilot Holes


Drill the holes with a 8 mm (5/16 in) drill bit.



3 | Install Anchors and Mount

Push anchors into holes until flush with the wall.

Place the wall mount over the anchors and screw the mount into the wall until securely attached.

**4 | Plug In Cables and Power Supply**

Plug the Starlink, AC and Ethernet cables into the power supply. Slide the power supply into the mount, making sure the top clip snaps into place.

Finish installation by routing the Ethernet cable to your router install location, connect to router and plug in router and power supply into your power source.

